

# Foxboro Evo™ Process Automation System


## Product Specifications

# Foxboro®

by Schneider Electric

PSS 31H-2Z18

### FBM218 HART® Communication Redundant Output Module



The FBM218 provides eight channels that support the HART® protocol and/or 4-20 mA outputs (the signals are electrically compatible) user-selectable on a per channel basis. A pair of FBM218 modules supports continued plant operation in the presence of a single failure and through the simple maintenance replacement.

#### OVERVIEW

The HART Communication Redundant Output Module (FBM218) contains eight channel-isolated outputs. The FBM218 supports any mix of standard 4 to 20 mA devices and HART devices.

A pair of the modules combines to provide redundancy at the Fieldbus Module level, with field outputs wired to one termination assembly (see Figure 1). In this configuration, one FBM218 is the Master, and the other is the Tracker.

The FBM218 serves as a HART communications field device host, enabling the Foxboro Evo™ system to request and receive two digital messages per second from each field device.

The message pass-through capability can be used to support HART universal, common practice, and device-specific commands, but not the burst communication mode. These commands are implemented using the Intelligent Field Device Configurator

FoxCom™ and HART™ Protocols (IFDC — refer to PSS 21S-8A2 B3 for details).

The module provides an isolated power supply for each channel.

## FEATURES

Key features of the FBM218 module are:

- ▶ Eight channel-isolated outputs, each providing one of the following outputs:
  - Standard 4 to 20 mA analog output signal
  - Digital HART Frequency Shift Keying (FSK) signal superimposed on a 4 to 20 mA analog output signal.
- ▶ Module pair offers redundancy at the FBM level
- ▶ FSK modem dedicated to each output channel for bi-directional digital communications with a HART field device

- ▶ Support for HART universal commands necessary to interface the field device with the Foxboro Evo system database
- ▶ Galvanic isolation of all output channels from each other, and from ground and module logic
- ▶ Compact, rugged design suitable for enclosure in Class G3 (harsh) environments
- ▶ Termination Assemblies (TAs) for locally or remotely connecting field wiring to the FBM218.

## PHYSICAL DESIGN

The FBM218 has a modular design, with a rugged extruded aluminum exterior for physical protection of the circuits. Enclosures specially designed for mounting the FBMs provide various levels of environmental protection, up to harsh environments per ISA Standard S71.04.




Figure 1. Redundant Module Configuration

## REDUNDANT ANALOG OUTPUTS

Each output channel drives an external load and produces a 0 to 20 mA output. Outputs are combined in series through the redundant adapter. The microprocessor of each module executes the analog I/O application program, plus security routines that validate the health of the FBM.

If a failure is detected in one of the modules, its output is driven to 0 mA and the corresponding channel in the good module automatically continues supplying the proper current to the output current loop.

Configurable options in the modules for output security include Fail-Safe Action (Hold/Fallback), Analog Output Fail-Safe Fallback Data (on a per channel basis), Fieldbus Fail-Safe Enable, and Fieldbus Fail-Safe Delay Time. The Analog Output Fail-Safe Fallback Data option must be set for 0 mA output. This removes one of the pair of redundant output channels from service for detectable problems such as a module not properly receiving output writes or not passing security tests on FBM microprocessor writes to output registers. Setting of the Analog Output Fail-Safe Fallback Data option for 0 mA output also minimizes the possibility of a “fail high” result.

## VISUAL INDICATORS

Light-emitting diodes (LEDs) incorporated into the front of the module provide visual indication of the module's operational status, and communication activity of the channels. Two additional LEDs provide the master or tracker status of the modules.

## EASY REMOVAL/REPLACEMENT

The module can be removed/replaced without removing field device termination cabling, power, or communications cabling.

## FIELDBUS COMMUNICATION

A Fieldbus Communication Module or a Control Processor interfaces the redundant 2 Mbps module Fieldbus used by the FBMs. The FBM218 module accepts communication from either path (A or B) of the redundant 2 Mbps fieldbus – should one path fail or be switched at the system level, the module continues communication over the active path.

## MODULAR BASEPLATE MOUNTING

The module mounts on a modular baseplate, which accommodates up to four or eight FBMs. The modular baseplate is either DIN rail mounted or rack mounted, and includes signal connectors for redundant fieldbus, redundant independent dc power, and termination cables.

Redundant modules must be located in adjacent positions on the baseplate (positions 1 and 2, 3 and 4, 5 and 6, or 7 and 8). To achieve redundancy, a redundant adapter module is placed on the two adjacent baseplate termination cable connectors to provide a single termination cable connection (see Figure 1). A single termination cable connects from the redundant adapter to the associated termination assembly (TA).

## TERMINATION ASSEMBLIES

Field output signals connect to the FBM subsystem via DIN rail mounted TAs. The TAs used with the FBM218 are described in “TERMINATION ASSEMBLIES AND CABLES” on page 8.

## FUNCTIONAL SPECIFICATIONS

### Field Device Channels

#### SUPPORTED HART INSTRUMENT TYPES

HART instruments compliant to Version 5, 6, or 7 of the HART specifications may be used

#### INTERFACE

8 isolated output channels

#### COMMUNICATIONS TO THE DEVICE

Point-to-point, master/slave, asynchronous, half-duplex, at 1200 baud.

#### ERROR CHECKING

Parity on each byte, and 32-bit CRC error checking on each message

#### SPEED

2 messages per second

#### FASTEST ALLOWED ECB BLOCK PERIOD

100 msec - However, it is recommended that you refer to the *Sizing Guidelines and Excel Workbook* appropriate for your Control Processor to determine the optimal loading for a 100 msec Block Processing Cycle (BPC).

#### MAXIMUM DISTANCE (FBM218 TO DEVICE)

Meets HART FSK physical layer specification HCF\_SPEC-54, Revision 8.1 [up to 3030 m (10000 ft)]<sup>(1)</sup>

#### CURRENT OUTPUTS

##### *Analog Accuracy (Includes Linearity)*

±0.05% of span (between 4 mA and 20 mA)

##### *Output Load*

750 Ω maximum

##### *Maximum Rate of Change*

20 mA in 60 milliseconds

##### *Resolution*

13 bits

#### LOOP POWER SUPPLY PROTECTION

Each channel is galvanically isolated, current limited, and voltage regulated.

All outputs are limited by their design to about 25 mA. If the output FET shorts, the output current could increase up to 100 mA. In normal operation the FBM outputs a constant current into a 0 to 750 ohm load.

#### ISOLATION

The channels are galvanically isolated (both optical and transformer isolation) from each other, and from ground and module logic. The module withstands, without damage, a potential of 600 V ac applied for one minute between the isolated channels and earth (ground).

#### CAUTION

This does not imply that these channels are intended for permanent connection to voltages of these levels. Exceeding the limits for input voltages, as stated elsewhere in this specification, violates electrical safety codes and may expose users to electric shock.

### Fieldbus Communication

Communicates with its associated FCM or FCP via the redundant 2 Mbps HDLC fieldbus

### Power Requirements

#### INPUT VOLTAGE RANGE (REDUNDANT)

24 V dc ±5%

#### CONSUMPTION

7 W (maximum)

#### HEAT DISSIPATION

5 W (maximum)

### Calibration

Calibration of the module and termination assembly is not required.

(1) The maximum allowable distance decreases when the loop is operated through an intrinsic safety barrier. The maximum distance of the field device from the FBM is a function of compliance voltage (19 V dc at 20.4 mA), wire and load resistance, and voltage drop at the field device.

## FUNCTIONAL SPECIFICATIONS (CONTINUED)

## Regulatory Compliance

## ELECTROMAGNETIC COMPATIBILITY (EMC)

*European EMC Directive 89/336/EEC*Meets: EN 50081-2 Emission standard  
EN 50082-2 Immunity standard  
EN 61326 Annex A (Industrial  
Levels)*CISPR 11, Industrial Scientific and Medical  
(ISM) Radio-frequency Equipment -  
Electromagnetic Disturbance Characteristics  
- Limits and Methods of Measurement*

Meets Class A Limits

*IEC 61000-4-2 ESD Immunity*

Contact 4 kV, air 8 kV

*IEC 61000-4-3 Radiated Field Immunity*  
10 V/m at 80 to 1000 MHz*IEC 61000-4-4 Electrical Fast  
Transient/Burst Immunity*2 kV on I/O, dc power and communication  
lines*IEC 61000-4-5 Surge Immunity*2 kV on ac and dc power lines; 1 kV on I/O  
and communications lines*IEC 61000-4-6 Immunity to Conducted  
Disturbances Induced by Radio frequency  
Fields*10 V (rms) at 150 kHz to 80 MHz on I/O,  
dc power and communication lines*IEC 61000-4-8 Power Frequency Magnetic  
Field Immunity*

30 A/m at 50 and 60 Hz

## PRODUCT SAFETY

*Underwriters Laboratories (UL) for U.S. and  
Canada*UL/UL-C listed as suitable for use in  
UL/UL-C listed Class I, Groups A-D;  
Division 2; temperature code T4 enclosure  
based systems. These modules are also UL  
and UL-C listed as associated apparatus for  
supplying non-incendive communication  
circuits for Class I, Groups A-D hazardous  
locations when connected to specified  
Foxboro Evo processor modules as  
described in the *Standard and Compact  
200 Series Subsystem User's Guide*  
(B0400FA). Communications circuits also  
meet the requirements for Class 2 as defined  
in Article 725 of the National Electrical Code  
(NFPA No.70) and Section 16 of the  
Canadian Electrical Code (CSA C22.1).  
Conditions for use are as specified in the  
*Standard and Compact 200 Series  
Subsystem User's Guide* (B0400FA).*European Low Voltage Directive 73/23/EEC  
and Explosive Atmospheres (ATEX) directive  
94/9/EC*CENELEC (DEMKO) certified as EEx nA IIC  
T4 for use in CENELEC certified Zone 2  
enclosure certified as associated apparatus  
for supplying non-incendive field circuits for  
Zone 2, Group IIC, potentially explosive  
atmospheres when connected to specified  
Foxboro Evo processor modules as  
described in the *Standard and Compact  
200 Series Subsystem User's Guide*  
(B0400FA). Also, see Table 1 on page 9.

## ENVIRONMENTAL SPECIFICATIONS<sup>(2)</sup>

### Operating

#### TEMPERATURE

##### *Module*

-20 to +70°C (-4 to +158°F)

##### *Termination Assembly*

###### PVC

-20 to +50°C (-4 to +122°F)

#### RELATIVE HUMIDITY

5 to 95% (noncondensing)

#### ALTITUDE

-300 to +3,000 m (-1,000 to +10,000 ft)

### Storage

#### TEMPERATURE

-40 to +70°C (-40 to +158°F)

#### RELATIVE HUMIDITY

5 to 95% (noncondensing)

#### ALTITUDE

-300 to +12,000 m (-1,000 to +40,000 ft)

### Contamination

Suitable for use in Class G3 (Harsh) environments as defined in ISA Standard S71.04, based on exposure testing according to EIA Standard 364-65, Class III.

### Vibration

7.5 m/S<sup>2</sup> (0.75 g) from 5 to 500 Hz

---

(2) The environmental limits of this module may be enhanced by the type of enclosure containing the module. Refer to the applicable Product Specification Sheet (PSS) which describes the specific type of enclosure that is to be used.

## PHYSICAL SPECIFICATIONS

### Mounting

#### MODULE

The FBM218 mounts on a baseplate. The baseplate can be mounted on a DIN rail (horizontally or vertically), or horizontally on a 19-inch rack using a mounting kit. Refer to PSS 31H-2SBASEPLT for details.

#### TERMINATION ASSEMBLY

The TA mounts on a DIN rail and accommodates multiple DIN rail styles including 32 mm (1.26 in) and 35 mm (1.38 in).

### Weight

#### MODULE

284 g (10 oz) approximate

#### TERMINATION ASSEMBLY

##### *Compression*

181 g (0.40 lb) approximate

##### *Ring Lug*

249 g (0.55 lb) approximate

### Dimensions – Module

#### HEIGHT

102 mm (4 in)

114 mm (4.5 in) including mounting lugs

#### WIDTH

45 mm (1.75 in)

#### DEPTH

104 mm (4.11 in)

### Part Numbers

#### FBM218 MODULE

P0922VW

#### TERMINATION ASSEMBLIES

See "FUNCTIONAL SPECIFICATIONS – TERMINATION ASSEMBLIES" on page 8

#### REDUNDANT ADAPTER

P0916QD

### Termination Cables

#### CABLE LENGTHS

Up to 30 m (98 ft)

#### CABLE MATERIALS

Polyurethane or Low Smoke Zero Halogen (LSZH)

#### TERMINATION CABLE TYPE

Type 1 – See Table 2 on page 10

#### CABLE CONNECTION – TA

25-pin male D-subminiature

### Construction – Termination Assembly

#### MATERIAL

Polyvinyl Chloride (PVC), compression PVC, ring lug

#### FAMILY GROUP COLOR

Green – communication

#### TERMINAL BLOCKS

##### *Outputs*

3 tiers, 8 positions

### Field Termination Connections

#### COMPRESSION-TYPE ACCEPTED WIRING SIZES

##### *Solid/Stranded/AWG*

0.2 to 4 mm<sup>2</sup>/0.2 to 2.5 mm<sup>2</sup>/24 to 12 AWG

##### *Stranded with Ferrules*

0.2 to 2.5 mm<sup>2</sup> with or without plastic collar

#### RING-LUG TYPE ACCEPTED WIRING SIZES

#6 size connectors (0.375 in (9.5 mm))

0.5 to 4 mm<sup>2</sup>/22 AWG to 12 AWG

## TERMINATION ASSEMBLIES AND CABLES

Field output signals connect to the FBM subsystem via DIN rail mounted Termination Assemblies, which are **electrically passive**. TAs for the FBM218 are available in the following forms:

- ▶ Compression screw type using Polyvinyl Chloride (PVC) or Polyamide material
- ▶ Ring lug type using PVC material

See the following “FUNCTIONAL SPECIFICATIONS – TERMINATION ASSEMBLIES” for a list of TAs used with the FBM218.

The FBM218 provides sufficient loop resistance to allow use of the HART Hand-Held Terminal, or PC20 Intelligent Field Device Configurator (PSS 2A-1Z3 E).

A removable termination cable connects the DIN rail mounted TA to the FBM via a field connector on the baseplate in which the FBM is installed. Termination cables are available in the following materials:

- ▶ Polyurethane
- ▶ Low Smoke Zero Halogen (LSZH).

Termination cables are available in a variety of lengths, up to 30 meters (98 feet), allowing the Termination Assembly to be mounted in either the enclosure or in an adjacent enclosure. See Table 2, for a list of termination cables used with the TAs for the FBM218.

## FUNCTIONAL SPECIFICATIONS – TERMINATION ASSEMBLIES

FBM Type	Output Signal	TA Part Number	TA Part Number	Termination	TA Cable	TA Certification
		PVC <sup>(a)</sup>	PA <sup>(a)</sup>	Type <sup>(b)</sup>	Type <sup>(c)</sup>	Type <sup>(d)</sup>
FBM218	8 output channels, 4 to 20 mA analog signal, alone or with HART signal superimposed	P0917XV P0926EK	P0926SP	C RL	1	1, 2

(a) PVC is polyvinyl chloride rated from -20 to +50°C (-4 to +122°F). PA is polyamide rated from -20 to +70°C (-4 to +158°F).

(b) C = TA with compression terminals; RL = TA with ring lug terminals.

(c) See Table 2 for cable part numbers and specifications.

(d) See Table 1 for Termination Assembly certification definitions.

**Table 1. Certification for Termination Assemblies**

Type	Certification <sup>(a)</sup>
Type 1	TAs are UL/UL-C listed as suitable for use in Class I; Groups A-D; Division 2 temperature code T4 hazardous locations. They are CENELEC (DEMKO) certified EEx nA IIC T4 for use in Zone 2 potentially explosive atmospheres.
Type 2	TAs are UL/UL-C listed as associated apparatus for supplying non-incendive field circuits Class I; Groups A-D; Division 2 hazardous locations when connected to specified 200 Series FBMs and field circuits meeting entity parameter constraints specified in <i>Standard and Compact 200 Series Subsystem User's Guide</i> (B0400FA). They are also CENELEC (DEMKO) certified as associated apparatus for supplying field circuits for Group IIC, Zone 2 potentially explosive atmospheres. Field circuits are also Class 2 limited energy (60 V dc, 30 V ac, 100 VA or less) if customer-supplied equipment meets Class 2 limits.

- (a) All TAs are UL/UL-C listed to comply with applicable ordinary location safety standards for fire and shock hazards. Hazardous location types comply with ATEX directive for II 3 G use. They also comply with the requirements of the European Low Voltage Directive. All listings/certifications require installation and use within the constraints specified in *Standard and Compact 200 Series Subsystem User's Guide* (B0400FA) and the conditions stated in UL and DEMKO reports.

**Table 2. Cables Types and Part Numbers**

Cable Length m (ft)	Type 1 P/PVC <sup>(a)</sup>	Type 1 LSZH <sup>(b)</sup>	Type 1 H/XLPE <sup>(c)</sup>
0.5 (1.6)	P0916DA	P0928AA	P0916VA
1.0 (3.2)	P0916DB	P0928AB	P0916VB
2.0 (6.6)	P0931RM	P0928AC	P0931RR
3.0 (9.8)	P0916DC	P0928AD	P0916VC
5.0 (16.4)	P0916DD	P0928AE	P0916VD
10.0 (32.8)	P0916DE	P0928AF	P0916VE
15.0 (49.2)	P0916DF	P0928AG	P0916VF
20.0 (65.6)	P0916DG	P0928AH	P0916VG
25.0 (82.0)	P0916DH	P0928AJ	P0916VH
30.0 (98.4)	P0916DJ	P0928AK	P0916VJ

(a) P/PVC is polyurethane outer jacket and semi-rigid PVC primary conductor insulation.

Temperature range: -20 to +80°C (-4 to +176°F).

(b) Low smoke zero halogen or low smoke free of halogen (LSZH) is a material classification used for cable jacketing. LSH is composed of thermoplastic or thermoset compounds that emit limited smoke and no halogen when exposed to high sources of heat. Temperature range: -40 to +105°C (-40 to +221°F).


(c) H/XLPE is Hypalon outer jacket and XLPE (cross-linked polyethylene) primary conductor insulation.

Temperature range: -40 to +90°C (-40 to +194°F). Hypalon cables are no longer available for purchase.


## DIMENSIONS – NOMINAL

[mm]  
in

Compression Termination Assembly



Ring Lug Termination Assembly



(a) Overall width – for determining DIN rail loading.

(b) Height above DIN rail (add to DIN rail height for total).

**RELATED PRODUCT SPECIFICATION SHEETS**

<b>PSS Number</b>	<b>Description</b>
PSS 31H-2S200	Standard 200 Series Subsystem Overview
PSS 31H-2CERTS	Standard and Compact 200 Series I/O - Agency Certifications
PSS 31H-2SBASEPLT	Standard 200 Series Baseplates

**Foxboro®**

**by Schneider Electric**

Invensys Systems, Inc  
10900 Equity Drive  
Houston, TX 77041  
United States of America  
<http://www.invensys.com>

Global Customer Support  
Inside U.S.: 1-866-746-6477  
Outside U.S.: 1-508-549-2424  
Website: <https://support.ips.invensys.com>

Copyright 2014 Invensys Systems, Inc.  
All rights reserved.  
Invensys is now part of Schneider Electric.

Invensys, Foxboro, Foxboro Evo, and Foxboro Evo logo  
are trademarks owned by Invensys Limited, its  
subsidiaries and affiliates.

All other trademarks are the property of their respective  
owners.

MB 031

0914